

# LogiLink®

## Audio Converter

Digital SPDIF/COAX to Analog

Art. No.: CA0100






Experience premium hearing quality with LogiLink Audio Converter, converting digital Coaxial or Toslink audio signals to analog L/R audio signals.

### Features:

- » 24-bit S/PDIF incoming bit stream on left and right channels
- » Output sampling rate at 32, 44.1, 48 and 96 kHz
- » Provides electromagnetic-noise-free transmission
- » Easy to install and simple to operate




Blu-ray/DVD



Speaker



\*The specifications and pictures are subject to change without prior notice.  
\*All trade names referenced are the registered trademarks of their respective owners.



Made in China

## Specification:

Input Ports	1x Toslink (SPDIF/Optical), 1x digital coaxial (RCA) female
Output Ports	2x Cinch (L/R audio)
Sampling Rates	32, 44.1, 48, 96 kHz
SPDIF Interface	Yes
Umcompressed Audio	LPCM 2.0
Power Supply	DC 5 V/1 A (5 W max.)
Power Consumption	0.5 W max.
Operating Temperature	0–70°C
Operating Humidity	10–85 % RH (no condensation)
Housing Material	Metal
Dimensions	5.1 x 4.1 x 2.6 cm
Weight	0.07 kg

## Specification of External Power Supply:

Input Voltage	100–240 V, 50/60 Hz 0.2 A max.
Output Power	5 V/1 A, 5 W
DC Plug	5.5 x 2.1 mm
Dimensions	51 x 35 x 59 mm
Cable Length	1.2 m
Weight	0.07 kg



## Package Contents:

- » 1 x Audio Converter
- » 1 x Power Supply
- » 1 x User Manual

## Package Information:

- » Packing Dimension: 149 x 110 x 40 mm
- » Packing Weight: 0.26 kg
- » Carton Dimension: 575 x 235 x 340 mm
- » Carton Q'ty: 50 pcs
- » Carton Weight: 11.1 kg



\*The specifications and pictures are subject to change without prior notice.  
\*All trade names referenced are the registered trademarks of their respective owners.



Made in China